

## **EPO Procedure for IBM z800 eServer (2066-0LF)**

Document date: 9/5/03

Author: Jason J. Herne

For this procedure, use the HMC (black console next to z800). If the HMC is not operational, use one of the SE's (IBM laptops) located behind the front cover of the machine.

1. If you do not see a login screen, open the "Hardware Management Console Application"

- Double click on the "Hardware Management Console Application" icon on the desktop.

2. Log on to HMC Application

username: OPERATOR

password: \*\*\*\*\*

3. Deactivate the z/VM LPAR

- Double click on the "Task List" icon in the "Views" area.
- Double click on the "Daily" icon. (Right window should now say "Daily" at the top)
- Double click on the "Groups" icon in the Views area.
- Double click on the "CPC Images" icon.
- Select the "LPSYS" icon.
- Double click "Deactivate" from right window.
- Click YES.

4. Deactivate and power off the CPC

- Double click on the "Task List" icon in the "Views" area.
- Double click on the "Daily" icon. (Right window should now say "Daily" at the top)
- Double click on the "Groups" icon in the Views area.
- Double click on the "Defined CPC's" icon.
- Select the "P001A8CA" icon.
- Double click "Deactivate" from right window.
- Click YES.

5. Power off the machine's dual power supplies.

- Open the BACK of the z800.
- Locate the two power supply on/off switches on the lower right hand side of the machine.
- Flip the two switches one at a time.

6. Shutdown HMC (DO NOT do this on an SE, this is an HMC step only)

- Right click on desktop.
- Select Shutdown.
- Click OK.

7. Inform administrator: [hernejj@clarkson.edu](mailto:hernejj@clarkson.edu) (268-2313)